

Fitting replacement IC1 part no QF4PCB7

Remove old battery, R12, R14, D21, D22, C16, IC1 and IC1 base.

Clean Pcb where necessary. Fit new IC base and plug in QF4PCB7 with notch on the PCB towards chassis, see the picture!

Storing stations, 14 in total:

Store 1st seven positions:

Step 1: press "tune" button

Step 2: tune to frequency required

Step 3: press and hold "tune" button, press preselected button and hold until green LED lights (as original Quad unit)

Store 2nd seven positions:

Now press preselected button again and follow steps 1 to 3 again.

